



powerful solutions in battery charging

Instructions for bringing a charger onto an existing network.

If the charger is connected to a different network, first leave the existing network. Before programming disconnect the battery from the charger.

- 1 Press OK
- 2 Scroll to Login and login in using password 2451
- 3 Select Service and press OK
- 4 Scroll to Radio menu
- 5 Scroll to Leave network and press OK

If the charger is not connected to a different network Enable the Radio function

- 1 Press OK
- 2 Scroll to Login and login in using password 2451
- 3 Select Service and press OK
- 4 Scroll to Radio menu
- 5 Scroll to Function and press OK
- 6 Scroll to select Enabled and press OK
- 7 Press escape to return to Radio menu

Before the charger can be connected to the network an existing network charger must enable joining. Go to the existing networked charger that is closest to the new charger and follow below. ** (restart here from last step below if necessary).

- 1 Press OK
- 2 Scroll to Login and login in using password 2451
- 3 Select Service and press OK
- 4 Scroll to Display menu and press OK
- 5 Scroll to Backlight and press OK
- 6 Using arrow keys set Backlight to 60 and press OK
- 7 Press ESC
- 8 Scroll to Radio menu
- 9 Scroll to Join Enable and press OK

As quickly as possible go to the new charger and follow below.

- 1 If not still in Radio menu, navigate menus as described above to get to the Radio menu.
- 2 Scroll to Join Network and press OK
- 3 If prompted, enter Password 2451
- 4 If the message Success is displayed the charger has joined the network and you are done.
- 5 If the message Failed is displayed go back to "***" and repeat all steps as quickly as possible to avoid any menu timeouts.